


SPEAKERS FOR COMPUTER, TELEPHONE, ALARM, TOY...

(NdFeB MAGNET)

Impedence could be from 4 OHM to 1000 OHM



ELS28NT




ELS283NT



ELS30NT




ELS360NT



ELS363NT



ELS401NT



ELS402NT



ELS403NT



ELS502NT

No.	Model	Size		IMP. Ω	Resonant Freq. Hz	Freq. Range Hz (fo)	Sensitivity dB (+/- 3dB)	Power Input		Magnet Size mm	Speaker N.W. g	Packing PCS/NW/GW
		Dia. mm	High mm					Nom mW	Max mW			
1	ELS28NT	28	4.6	8	500	6K	85	0.1	0.2	9.5 × 1.5	4.8	1000/7.6/8.6
2	ELS283NT	28	5.3	8	350	20K	80	0.3	0.5	9.5 × 1.5	4.8	1000/7/8
3	ELS30NT	30	5.3	8	500	7.8K	80	0.2	0.3	9.5 × 1.5	5.6	1000/7.6/8.6
4	ELS360NT	36	5.8	8	420	4K	80	0.2	0.3	9.5 × 1.5	6.4	1000/11/12
5	ELS363NT	36	4.3	8	420	6.6K	77	0.3	0.5	12.5 × 1.5	7.4	1000/12/13
6	ELS401NT	40	7	8	480	9.4K	79	0.2	0.3	9.5 × 1.5	8.2	1000/13/14
7	ELS402NT	40	6.2	8	520	5K	74	0.2	0.3	12.5 × 1.5	9.4	1000/14/15
8	ELS403NT	40	4.2	8	500	6.5K	77	0.2	0.3	12.5 × 1.5	9.6	1000/14/15
9	ELS502NT	50	7.5	8	480	8.6K	83	0.2	0.3	12.5 × 1.5	12.4	800/12/13

■ TEST CONDITION: 0.1 W, at MIC. 50cm